



# Premiere 8310L

## Specifications

<b>Processor</b>	Supports Socket LGA 775 for Intel® Core 2 Quad / Core 2 Duo / Pentium / Celeron processors Supports Intel® Hyper-Threading Technology Supports Intel® Dual Core Technology to 800MHz and up Supports FSB 800 / 1066 / 1333 MHz
<b>Chipset</b>	Intel® G31+ ICH7
<b>Audio</b>	Integrated 7.1 channels HD audio codec Realtek® ALC888
<b>Video</b>	Integrated Intel® Graphics Media Accelerator (GMA) 3100
<b>System Memory</b>	<b>Supports two DDR2 memory modules, up to 4GB</b> Supports Dual channel memory architecture Supports DDR2 667/800 memory interface
<b>On-Board IDE</b>	Supports 1 Ultra ATA-100 port Supports 4 SATAII-300 ports
<b>Standard Diskette Size</b>	3.25"/1.44MB FDD
<b>Optical Drive</b>	52x CD-ROM Drive CD-RW Drive (optional)
<b>Network Interface</b>	<b>Integrated Realtek® RTL8111C 10/100/1000 Mb/s LAN</b>
<b>Modem</b>	56kbps V.92 Internal PCI Fax/Modem (optional)
<b>Expansion Slots</b>	<b>One PCI Express x 16 slot</b> Two PCI 2.3 32-bit PCI bus slots
<b>Drive Bays</b>	Two 5.25" for CD-ROM Drive One 3.5" for FDD Two 3.5" (hidden) for HDD
<b>I/O Interface</b>	2 PS/2 ports (For PS/2 Keyboard & PS/2 Mouse) 1 Parallel port 2 Serial ports (COM1 onboard and COM2 via pin header/optional) 1 VGA Port 8 USB 2.0 ports (4 rear, 4 optional) 1 x 3 in 1 Audio Jack 1 RJ45 Connector
<b>Chassis</b>	Micro Tower ATX
<b>Keyboard</b>	Wearnes Keyboard
<b>Mouse</b>	Wearnes Mouse
<b>Monitor</b>	Wearnes 15" SVGA Digital Monitor Wearnes 17" SVGA Digital Monitor (optional) Wearnes 15.1" TFT-LCD Monitor (optional)
<b>Speaker</b>	Wearnes Active Speaker (optional) Wearnes Active Speaker with Subwoofer (optional)
<b>Power Supply</b>	300 Watt
<b>Operating System Supported</b>	Windows® XP Home/Professional Edition Windows® Vista Starter/Home Basic/Home Premium/Business/Ultimate Edition

\*\*\*7529\*\*\*