



# Premiere 7865LG

## Specifications

<b>Processor</b>	Supports Intel® Pentium 4 / Celeron D processors in LGA775 package Supports Intel Hyper-Threading Technology Supports FSB 533/800MHz
<b>Chipset</b>	Intel® 865GV chipset
<b>Cache L2 Memory</b>	1MB L2 cache, depends on Processor
<b>Audio</b>	Integrated AC'97 codec supported 6 channels software audio codec Realtek ALC655
<b>Video</b>	Integrated Intel® Graphics Media Accelerator (GMA) 900
<b>System Memory</b>	Supports two DDR memory modules, up to 2GB Supports Dual channel memory architecture Supports DDR 400 memory interface
<b>On-Board IDE</b>	Supports 2 Ultra ATA-100 ports Supports 2 Serial ATA-150 ports
<b>Standard Diskette Size</b>	3.25"/1.44MB FDD
<b>Optical Drive</b>	52x CD-ROM Drive CD-RW Drive (optional)
<b>Network Interface</b>	Integrated Realtek® 8100C 10/100 LAN
<b>Modem</b>	<a href="#">56kbps V.92 Internal PCI Fax/Modem (optional)</a>
<b>Expansion Slots</b>	One AGR (Advance Graphics Riser) slot for compatible AGP VGA cards Two PCI 2.3 32-bit PCI bus slots (support 3.3v/5v PCI bus interface)
<b>Drive Bays</b>	Two 5.25" for CD-ROM Drive One 3.5" for FDD Two 3.5" (hidden) for HDD
<b>I/O Interface</b>	1 PS/2 keyboard & mouse 1 parallel port 1 serial ports 1 VGA Port 8 USB 2.0 ports (4 rear, 4 optional) 1 line in, line out, microphone in 1 RJ45 connector
<b>Chassis</b>	Micro Tower ATX
<b>Keyboard</b>	Wearnes Keyboard
<b>Mouse</b>	Wearnes Mouse
<b>Monitor</b>	Wearnes 15" SVGA Digital Monitor <a href="#">Wearnes 17" SVGA Digital Monitor (optional)</a> <a href="#">Wearnes 15.1" TFT-LCD Monitor (optional)</a>
<b>Speaker</b>	<a href="#">Wearnes Active Speaker (optional)</a> <a href="#">Wearnes Active Speaker with Subwoover (optional)</a>
<b>Power Supply</b>	250 Watt
<b>Operating System Supported</b>	Windows® 2000 Professional Windows® XP Home/Professional Edition
<b>Limited Warranty Period</b>	Three year service & one spare part

\*\*\*7101\*\*\*