



# Premiere 7915L2

## Specifications

<b>Processor</b>	Supports Intel® Pentium 4 / Celeron D processors in LGA775 package Supports Intel Hyper-Threading Technology Supports FSB 533/800MHz
<b>Chipset</b>	<b>Intel® 915GV chipset</b>
<b>Cache L2 Memory</b>	1MB L2 cache, depends on Processor
<b>Audio</b>	Integrated AC'97 codec supported 6 channels software audio codec Realtek ALC655
<b>Video</b>	Integrated Intel® Graphics Media Accelerator (GMA) 900
<b>System Memory</b>	<b>Supports four DDR2 memory modules, up to 4GB</b> Supports Dual channel memory architecture <b>Supports DDR2 400/533 memory interface</b>
<b>On-Board IDE</b>	<b>Supports 1 Ultra ATA-100 port</b> Supports 4 Serial ATA-150 ports
<b>Standard Diskette Size</b>	3.25"/1.44MB FDD
<b>Optical Drive</b>	52x CD-ROM Drive <b>CD-RW Drive (optional)</b>
<b>Network Interface</b>	<b>Integrated Realtek® 8110S Gb LAN</b>
<b>Modem</b>	<b>56kbps V.92 Internal PCI Fax/Modem (optional)</b>
<b>Expansion Slots</b>	<b>Three PCI 2.3 32-bit PCI bus slots (support 3.3v/5v PCI bus interface)</b>
<b>Drive Bays</b>	Two 5.25" for CD-ROM Drive One 3.5" for FDD Two 3.5" (hidden) for HDD
<b>I/O Interface</b>	1 PS/2 keyboard & mouse 1 parallel port 2 serial ports, COM1 onboard and <b>COM2 via pin header (optional)</b> 1 VGA Port 8 USB 2.0 ports (4 rear, 4 optional) 1 line in, line out, microphone in 1 RJ45 connector
<b>Chassis</b>	Micro Tower ATX
<b>Keyboard</b>	Wearnes Keyboard
<b>Mouse</b>	Wearnes Mouse
<b>Monitor</b>	Wearnes 15" SVGA Digital Monitor <b>Wearnes 17" SVGA Digital Monitor (optional)</b> <b>Wearnes 15.1" TFT-LCD Monitor (optional)</b>
<b>Speaker</b>	<b>Wearnes Active Speaker (optional)</b> <b>Wearnes Active Speaker with Subwoofer (optional)</b>
<b>Power Supply</b>	300 Watt

\*\*\*7177\*\*\*