



Premiere 7915L

Specifications

| | |
|-----------------------------------|--|
| Processor | Supports Intel® Pentium 4 / Celeron D processors in LGA775 package Supports Intel Hyper-Threading Technology Supports FSB 533 / 800 MHz |
| Chipset | Intel® 915GL |
| Cache L2 Memory | 1MB L2 cache, depends on Processor |
| Audio | Integrated Realtek ALC880, 8-ch High-Definition Audio CODEC |
| Video | Integrated Intel® Graphics Media Accelerator (GMA) 900 |
| System Memory | Supports four DDR memory modules, up to 4GB Supports Dual channel memory architecture Supports DDR 333 / 400 memory interface |
| On-Board IDE | Supports 1 Ultra ATA-100 ports (Can connect up to two Ultra ATA drives) Supports 2 Serial ATA-150 ports |
| Standard Diskette Size | 3.25"/1.44MB FDD |
| Optical Drive | 52x CD-ROM Drive CD-RW Drive (optional) |
| Network Interface | Integrated Realtek® 8110S Gb LAN |
| Modem | 56kbps V.92 Internal PCI Fax/Modem (optional) |
| Expansion Slots | Three PCI 2.3 32-bit PCI bus slots |
| Drive Bays | Two 5.25" for CD-ROM Drive One 3.5" for FDD Two 3.5" (hidden) for HDD |
| I/O Interface | 1 PS/2 keyboard & mouse 1 parallel port 2 serial ports, Com1 on Rear IO, Com2 via pin header (IO bracket is optional) 1 VGA Port 8 USB 2.0 ports (4 rear, 4 optional) 1 Line-In / Line-Out / MIC-In / Rear Speaker Out / Center-Subwoofer Speaker 1 RJ45 connector |
| Chassis | Micro Tower ATX |
| Keyboard | Wearnes Keyboard |
| Mouse | Wearnes Mouse |
| Monitor | Wearnes 15" SVGA Digital Monitor Wearnes 17" SVGA Digital Monitor (optional) Wearnes 15.1" TFT-LCD Monitor (optional) |
| Speaker | Wearnes Active Speaker (optional) Wearnes Active Speaker with Subwoofer (optional) |
| Power Supply | 300 Watt |
| Operating System Supported | Windows® 2000 Professional Windows® XP Home/Professional Edition |

7133