



Premiere 8310L

Specifications

Processor	Supports Socket LGA 775 for Intel® Core 2 Quad / Core 2 Duo / Pentium / Celeron processors Supports Intel® Hyper-Threading Technology Supports Intel® Dual Core Technology to 800MHz and up Supports FSB 800 / 1066 / 1333 MHz
Chipset	Intel® G31+ ICH7
Audio	Integrated 7.1 channels HD audio codec Realtek® ALC888
Video	Integrated Intel® Graphics Media Accelerator (GMA) 3100
System Memory	Supports two DDR2 memory modules, up to 4GB Supports Dual channel memory architecture Supports DDR2 667/800 memory interface
On-Board IDE	Supports 1 Ultra ATA-100 port Supports 4 SATAII-300 ports
Standard Diskette Size	3.25"/1.44MB FDD
Optical Drive	52x CD-ROM Drive CD-RW Drive (optional)
Network Interface	Integrated Realtek® RTL8111B 10/100/1000 Mb/s LAN
Modem	56kbps V.92 Internal PCI Fax/Modem (optional)
Expansion Slots	One PCI Express x 16 slot One PCI Express x 1 slot Two PCI 2.3 32-bit PCI bus slots
Drive Bays	Two 5.25" for CD-ROM Drive One 3.5" for FDD Two 3.5" (hidden) for HDD
I/O Interface	1 PS/2 keyboard & mouse 1 parallel port via pin header 1 serial ports, COM1 onboard 1 VGA Port 8 USB 2.0 ports (4 rear, 4 optional) 1 Line-In / Line-Out / MIC-In / Rear Speaker Out / Center-Subwoofer Speaker 1 RJ45 connector
Chassis	Micro Tower ATX
Keyboard	Wearnes Keyboard
Mouse	Wearnes Mouse
Monitor	Wearnes 15" SVGA Digital Monitor Wearnes 17" SVGA Digital Monitor (optional) Wearnes 15.1" TFT-LCD Monitor (optional)
Speaker	Wearnes Active Speaker (optional) Wearnes Active Speaker with Subwoofer (optional)
Power Supply	300 Watt
Operating System Supported	Windows® 2000 Professional Windows® XP Home/Professional Edition Windows® Vista Starter/Home Basic/Home Premium/Business/Ultimate Edition

8310