

**BoldLINE**

## BoldLINE BL-C8800

### Specifications

<b>Processor &amp; Cache</b>	AMD Geode™ LX800 single core processor @ 500MHz, 0.9W L2 Cache 128KB
<b>Chipset</b>	Integrated AMD® Geode LX Processor's Chipset
<b>Graphics &amp; Video Module</b>	Integrated AMD® Geode LX processor's Graphics, Shared memory up to 128MB
<b>Main Memory</b>	512 MB DDR1 400MHz (PC3200) SODIMM, up to 1 GB
<b>Display</b>	8" TFT LCD 16:9 WXGA (1024 x 600 px)
<b>PC Cards Slot</b>	1 X PCMCIA
<b>Card Reader</b>	MMC/SD/MS 3-in-1 Card Reader
<b>Hard Disk Drive</b>	20GB 1.8" up to 60GB.
<b>Optical Drive</b>	DVD/CD-RW External Drive (optional)
<b>LAN / Modem</b>	Built-in 10/100 Ethernet LAN Built-in ZyDAS ZD1211T 802.11b/g WLAN card
<b>Bluetooth</b>	None
<b>I/O ports</b>	1 x Monitor (VGA) Port X 1 (15-pin D-Sub) 2 x High Speed USB2.0 Ports 1 x Microphone input 1 x Line Out / Headphone Output 1 x RJ-45 LAN Port
<b>Audio</b>	Integrated AC97 Codec, SoundBlaster Compatible
<b>Battery Type</b>	Li-Polymer 4 cells, 2200mAh approx. 2.5 hours
<b>AC Adapter</b>	12V DC, 2A, 36W / Input: 100 ~ 240V AC, 50/60Hz universal
<b>Dimension</b>	225(W) x 161(D) x 35(H) mm
<b>Weight</b>	Approx. 0.995 Kg

\*\*\*8800\*\*\*

[www.myboldline.com](http://www.myboldline.com)
*\*Specifications are subject to change without prior notice*