

Premiere 8410Ls



Specifications :

Processor	Supports Intel® Core 2 Extreme/Core 2 Quad/Core 2 Duo based processors	
Chipset	Intel® G41	
Audio	Embedded 7.1-channel High-Definition Audio	
Video	Integrated Intel® Graphics Media Accelerator X4500 (Intel® GMA X4500) 512MB Shared video memory (DVMT)	
System Memory	Supports two unbuffered DIMM DDR3 800/1066 SDRAM, 8GB Max	
On-Board IDE	Supports 1 Ultra ATA-100 port Supports 4 SATAII-300 ports	
Card Reader	Optional	
Optical Drive	Optional	
Network Interface	Integrated 10/100/1000 Mb/s (Gb) LAN	
Modem	Optional	
Expansion Slots	One PCI Express x16 slot One PCI Express x1 slot Two PCI 2.3 32-bit PCI bus slots	
Drive Bays	One 5.25" for CD/DVD Drive One 3.5" for FDD/Card Reader Two 3.5" (hidden) for HDD	
I/O Interface	Rear : <ul style="list-style-type: none"> • 2 PS/2, for keyboard & mouse • 1 VGA port • 4 USB 2.0 ports • 6 audio ports • 1 RJ45 connector 	Front : <ul style="list-style-type: none"> • 2 USB 2.0 ports • 2 Audio ports for High-definition headphone and microphone
Keyboard & Mouse	Wearnes USB Keyboard & Wearnes USB Optical Mouse	
Monitor	Wearnes 15" Widescreen LCD Monitor (Optional)	
Speaker	Optional	
Power Supply	250 Watt	
Chassis	Small Form Factor (SFF)	
Operating System	Supports Windows XP, Windows Vista & Windows 7	

** Specifications are subject to change without prior notice*