



# Quadra CNT-1012

## Specifications

<b>Processor</b>	Intel® Pentium® M processor (Dothan) FSB-533 1.6GHz to 2.13GHz FSB-400 1.6GHz to 1.8GHz
<b>L2 Cache</b>	2MB
<b>FSB</b>	533MHz/400MHz
<b>Chipset</b>	Intel® 915GM + ICH6-M
<b>Graphics &amp; Video Module</b>	Integrated Intel® GMA900 Graphics
<b>Main Memory</b>	DDR 256MB, up to 2GB
<b>Display</b>	12.1" TFT WXGA (1280X800)
<b>PC Cards Slot</b>	PCMCIA2.1, Compliant Type II X 1
<b>Card Reader</b>	MMC/SD/MS 3-in-1 Card Reader
<b>Hard Disk Drive</b>	Support 2.5" 9.5mm IDE HDD with Ultra ATA 100 40GB up to 120GB
<b>Optical Drive</b>	DVD-ROM/Combo
<b>LAN / Modem</b>	Built-in 10/100Mbps Ethernet LAN and Modem Module Built-in Mini-PCI Intel 802.11b / 802.11b/g WLAN card
<b>I/O ports</b>	Monitor (VGA) Port X 1 (15-pin D-Sub) High Speed USB2.0 Port X 3 Digital interface IEEE1394 Port X 1 Microphone input X 1 Headphone Output X 1 RJ-11 MODEM Port X 1 RJ-45 10/100 LAN Port X 1
<b>Audio</b>	AC97 2.2, SoundBlaster compatible
<b>Hot Keys</b>	4 instant launch keys, 4 buttons, e-mail, internet, wireless, user's define key
<b>Battery Type</b>	Li-Ion 4 cells, 2200mAh Appx. 2.5hrs
<b>AC Adapter</b>	19V DC, 65W / Input: 100 ~ 240V AC, 50/60Hz universal
<b>Dimension</b>	303(W) X 225(D) X 26-28(H)mm
<b>Weight</b>	1.8Kg

\*\*\*1012\*\*\*

1

