



# Quadra CNT-1034

## Specifications

<b>Processor</b>	Intel® Celeron M and Pentium M (Yonah) processor
<b>L2 Cache</b>	2 MB for Pentium M 1 M for Celeron M
<b>FSB</b>	533MHz / 667MHz
<b>Chipset</b>	Intel® 945GM + ICH7-M
<b>Graphics &amp; Video Module</b>	Integrated Intel® GMA 950 Graphics, 128 MB Shared Video Memory
<b>Main Memory</b>	512 MB DDR2 667 (PC2 5400), up to 2 GB
<b>Display</b>	15.4" TFT Super Glare Type WXGA (1280 x 800 px)
<b>PC Cards Slot</b>	1 X PCMCIA2.1 Type II
<b>Card Reader</b>	MMC/SD/MS/MS PRO 4-in-1 Card Reader
<b>Hard Disk Drive</b>	80 GB, up to 120 GB
<b>Optical Drive</b>	DVD/CD-RW Combo Drive (Internal)
<b>LAN / Modem</b>	Built-in Gigabit Ethernet LAN and Modem Module Built-in Intel® PRO 3945ABG 802.11 a/b/g WLAN card
<b>Bluetooth</b>	Built-in Bluetooth
<b>Web-camera</b>	Built-in 1.3M pixel Webcam
<b>I/O ports</b>	1 x Monitor (VGA) Port X 1 (15-pin D-Sub) 4 x High Speed USB2.0 Ports 1 x Digital interface IEEE 1394 Port 1 x Microphone input 1 x Line In 1 x Line Out / Headphone Output 1 x RJ-11 MODEM Port 1 x RJ-45 10/100 LAN Port 1 x TV Output / S-Video
<b>Audio</b>	Realtek ALC882, Supports 6 Channels High Definition Audio CODEC
<b>Hot Keys</b>	4 Quick Launch Buttons, E-mail, Internet, Wireless, & User's Define
<b>Battery Type</b>	Li-ion 6 cells, 4400mAh
<b>AC Adapter</b>	19V DC, 65W / Input: 100 ~ 240V AC, 50/60Hz universal
<b>Dimension</b>	358(W) x 259(D) x 27-33(H) mm
<b>Weight</b>	Approx. 2.5 Kg

\*\*\*1034\*\*\*

